



Pre-release Product Information

VHF MARINE TRANSCEIVER

IC-M35



"Automatic Volume Adjustment"

"Noise Canceling Mic"

"Loud, Instant Maximum Audio"

CLEAR VOICE BOOST

(Clear Voice + Voice Boost)

In marine environments there are many sources of noise that can affect the quality of your communication, such as engine noise, roar of waves and more. The IC-M35 constantly transmits clear voice and provides boosted audio even in those circumstances and ensures your conversation is sent and received as clearly as possible no matter how noisy the background is!

And yes, it floats too!

Continuing the legacy from the IC-M33, the IC-M35 floats for you to be able to retrieve it if you should ever lose it overboard. The IC-M35 floats even when the optional speaker microphone, HM-165 is attached.

BUOYANT

Waterproof

1m depth for 30 minutes



LOUD button

When you need an instant "boost" in the volume, a simple push of the "LOUD" button gives you full volume immediately. In addition, holding the "LOUD" button mutes the audio output.

Noise canceling microphone

The IC-M35 has a sub-microphone on the rear panel for noise cancellation. It inverts phase of ambient noise to reduce the affect of background noise from the transmitted signal.

Automatic volume adjustment

When in an engine room or high noise environment, the sub-microphone detects the ambient noise and the IC-M35 automatically increases the volume output to suit the surrounding environment.

Low power consumption

Although the IC-M35 delivers a high 6W RF output and 700mW audio output, its current saving circuit offers practical 8 hours* of operating time with the supplied 980mAh Lithium-Ion battery pack.
* Typical operation with Tx (Hi): Rx: standby=5:5:90

Large buttons and slim dimensions

Thanks to the large, easy-to-operate buttons, the IC-M35 provides intuitive operation. Pinched-waist slender body is easy for holding and carrying the radio, and is surprisingly compact for a floating radio.

Other features

- Waterproof construction equivalent to IPX7 (1m depth for 30 minutes)
- Dual/Tri-watch functions
- 4-step battery life indicator
- Auto scan function
- Instant access to Ch 16 or programmable call channel

SPECIFICATIONS

GENERAL	
• Frequency range	Tx : 156.000-161.450MHz Rx : 156.000-163.425MHz
• Usable channels	: INT, USA* channels; 70 programmable channels (* Depending on version)
• Current drain (at 7.4V DC) :	
Tx	6W output 1.5A typical
Rx	AF max.
	Internal speaker 300mA typical
	External speaker 200mA typical
	Power save 10mA typical
• Operating temperature range :	-15°C to +55°C
• Antenna impedance	: 50Ω (STUD)
• Dimensions (W×H×D)	: 62×139.5×43 mm (projections not included)
• Weight (approx.)	: 295g (with BP-252, MB-109 and antenna)

TRANSMITTER	
• Output power (Hi/Low)	: 6/1W 2/1W (with alkaline battery)
• Max. frequency deviation	: ± 5.0kHz
• Frequency error	: ± 1.5kHz
• Spurious emissions	: 0.25μW
• Adjacent channel power	: 70dB
• Audio harmonic distortion	: Less than 10% (at 60% dev.)
• Hum and noise ratio	: 40dB

RECEIVER	
• Sensitivity (20dB SINAD)	: -2dBμ emf typical
• Squelch sensitivity	: -6dBμ emf typical (threshold)
• Adjacent Ch. selectivity	: 70dB
• Spurious response	: 70dB
• Intermodulation rejection	: 68dB
• Hum and noise ratio	: 40dB
• Audio output power (at 10% distortion) :	
Internal speaker	700mW typical (with a 16Ω load)
External speaker	200mW (with an 8Ω load)


Supplied accessories

- Battery pack, BP-252
 - AC adapter, BC-174E*
 - Antenna, FA-SC58V
 - Battery case, BP-251 (UK version only)
 - Battery charger, BC-173
 - Belt clip, MB-109
 - Hand strap
- (* Not supplied depending on version.)


Measurements made in accordance with EN301-178-2. All stated specifications are subject to change without notice or obligation.

OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.



BP-251 BATTERY CASE
Battery case for AAA (LR03)×5 alkaline cells.
Output power: 2W.
BP-252 7.4V/980mAh Li-Ion BATTERY PACK
Provides 8 hours operating time (approx.).
(Typical operation with Tx (Hi): Rx: standby=5:5:90)



BC-173 DESKTOP CHARGER
+ **BC-174E AC ADAPTER**
Regularly charges the battery pack, BP-252 in 10 hours (approx.).



BC-162 DESKTOP CHARGER
+ **BC-145E/UK AC ADAPTER**
Rapidly charges the battery pack, BP-252 in 2 hours (approx.).



HM-165 SPEAKER-MICROPHONE
Waterproof construction equivalent to IPX7 (1 m depth for 30 min.).

- MB-109 BELT CLIP**
Alligator type.
Same as supplied.
- FA-SC58V ANTENNA**
Soft flexible antenna.
Same as supplied.
- CP-17L CIGARETTE LIGHTER CABLE**
For use with the BC-173 or BC-162 with an external DC power supply. (12-16 V DC required)

This device has not been approved by the appropriate authorities in each country. This device may not be sold or leased, or be offered for sale or lease, until approval has been obtained. All stated features, appearances, screen shots and specifications may be subject to change without notice. Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in the United States, the United Kingdom, Germany, France, Spain, Russia and/or other countries. All other trademarks are the properties of their respective holders.

Icom Inc. 1-1-32, Kami-minami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013 URL: <http://www.icom.co.jp/world/index.html>

Count on us!

Icom America Inc.
2380 116th Avenue NE,
Bellevue, WA 98004, U.S.A.
Phone : +1 (425) 454-8155
Fax : +1 (425) 454-1509
E-mail : sales@icomamerica.com
URL : <http://www.icomamerica.com>

Icom New Zealand
146A Harris Road, East Tamaki,
Auckland, New Zealand
Phone : +64 (09) 274 4062
Fax : +64 (09) 274 4708
E-mail : inquiries@icom.co.nz
URL : <http://www.icom.co.nz>

Icom (UK) Ltd.
Unit 9, Sea St., Herne Bay,
Kent, CT6 8LD, U.K.
Phone : +44 (01227) 741741
Fax : +44 (01227) 741742
E-mail : info@icomuk.co.uk
URL : <http://www.icomuk.co.uk>

Asia Icom Inc.
6F No. 68, Sec. 1 Cheng-Teh Road,
Taipei, Taiwan, R.O.C.
Phone : +886 (02) 2559 1899
Fax : +886 (02) 2559 1874
E-mail : sales@asia-icom.com
URL : <http://www.asia-icom.com>

Your local distributor/dealer:

Icom Canada
Glenwood Centre #150-6165 Highway 17,
Delta, B.C., V4K 5B8, Canada
Phone : +1 (604) 952-4266
Fax : +1 (604) 952-0090
E-mail : info@icomcanada.com
URL : <http://www.icomcanada.com>

Icom (Europe) GmbH
Communication Equipment
Himmelgeister Str. 100,
D-40225 Düsseldorf, Germany
Phone : +49 (0211) 346047
Fax : +49 (0211) 333639
E-mail : info@icomeurope.com
URL : <http://www.icomeurope.com>

Icom France s.a.s.
Zac de la Plaine,
1 Rue Brindejonn des Moulinais, BP 45804,
31505 Toulouse Cedex 5, France
Phone : +33 (5) 61 36 03 03
Fax : +33 (5) 61 36 03 00
E-mail : icom@icom-france.com
URL : <http://www.icom-france.com>

Icom (Australia) Pty. Ltd.
Unit 1 / 103 Garden Road,
Clayton, VIC 3168 Australia
Phone : +61 (03) 9549 7500
Fax : +61 (03) 9549 7505
E-mail : sales@icom.net.au
URL : <http://www.icom.net.au>

Icom Spain S.L.
Ctra. Rubi, No. 88 "Edificio Can Castanyer"
Bajos A 08174, Sant Cugat del Valles,
Barcelona, Spain
Phone : +34 (93) 590 26 70
Fax : +34 (93) 589 04 46
E-mail : icom@icomspain.com
URL : <http://www.icomspain.com>

Icom Polska
81-850 Sopot, ul. 3 Maja 54, Poland
Phone : +48 (58) 550 7135
Fax : +48 (58) 551 0484
E-mail : icompolksa@icompolksa.com.pl
URL : <http://www.icompolksa.com.pl>